

National Load Despatch Centre
Import of Punjab Transfer Capability for May 2023

Issue Date: 28th January 2023

Issue Time: 1500 Hrs

Revision No. 0

Date	Time Period in IST (hrs)	Total Transfer Capability (TTC)	Reliability Margin	Available Transfer Capability (ATC)	Long Term Access (LTA)/ Medium Term Open Access (MTOA) #	Margin Available for Short Term Open Access (STOA)	Changes in TTC w.r.t. Last Revision	Comments
1st May 2023 to 31st May 2023	00-08	9000	500	8500	4860	3640	0	
	08-18	9000	500	8500	4860	3640	0	
	18-24	9000	500	8500	4860	3640	0	
Limiting Constraints		<ol style="list-style-type: none"> 1. N-1 contingency of 400/220KV ICTs at Nakodar, Ludhiana. 2. Loading close to N-1 contingency limits of 400/220kV Patran, Malerkotla, Moga and Patiala ICTs 3. 220 kV underlying network at Ludhiana and Amritsar 4. Punjab SLDC to ensure minimum internal generation above 5000MW for this ATC/TTC. 5. ATC/TTC limits may be reviewed if Punjab SLDC is not able to manage loading of 400/220kV ICTs below N-1 contingency limit 						

National Load Despatch Centre
Import of Punjab Transfer Capability for May 2023

Revision No	Date of Revision	Period of Revision	Reason for Revision

Punjab critical ICTs			
SI No.	Name of Substation	ICTs Capacity (MVA)	N-1 Loading limit(MW)
1	Rajpura	3*500	1150
2	Nakodar	2*315	450
3	Moga	2*500+1*250+1*315	1185
4	Ludhiana	2*315+2*500	1265
023 to 31st	Amritsar	2*315+2*500	1220
#VALUE!	Patiala	2*315+1*500	855
#VALUE!	Patran	2*500	615
8	Dhuri	3*500	1090
<i>Loading of these ICTs should be kept within N-1 loading limit as specified above, loading of</i>			

Punjab critical lines			
Sl No.	Line	N-1 loading limit (MW)	Remarks
1	220kV Patran(PG)-Patran(PSTCL) ckt-1	115	Presently 220kV Patran(PSTCL) is being operated by opening 220kV Patran-Sunam and 220kV Patran-Bangan and entire load of 220kV Patran is being radially fed through 220kV Patran(PG)-Patran(PSTCL) D/C line, if loading stays above 115MW in each ckt then tripping of one line would lead to entire load loss at 66kV Patran
2	220kV Patran(PG)-Patran(PSTCL) ckt-2	115	
3	220kV Dhuri-Sunam ckt-1	135	If 220kV Bangan-Sunam is open. Line loading must be kept within N-1 loading limit.
4	220kV Dhuri-Sunam ckt-2	135	
023 to 31st	220kV Dhuri-Sunam ckt-1	150	
#VALUE!	220kV Dhuri-Sunam ckt-2	150	
#VALUE!	220kV Jalandhar-Kartarpur ckt-1		220kV Jalandhar-Kartarpur ckt-2 is out and entire load of Kartarpur and Kotlajungan is being radially fed through 220kV Jalandhar-Kartarpur ckt-1 (single HTLS line, thermal loading limit 380MW), tripping of this line would lead to entire load loss of Kartarpur and Kotlajungan.