National Load Despatch Centre Total Transfer Capability for July 2017

Issue Date: 27/3/2017 Issue Time: 1800 hrs Revision No. 0

Date	Time Period (hrs)	Total Transfer Capability (TTC)	Reliability Margin	Available Transfer Capability (ATC)	Long Term Access (LTA)/ Medium Term Open Access (MTOA) #	Margin Available for Short Term Open Access (STOA)	Changes in TTC w.r.t. Last Revision	Comments
1st July 2017 to	00-06				55	1945		
31st July 2017		2500	500	2000				
1st July 2017 to 31st July 2017	00-24	8550	500	8050	7951	99		
	00-06	2000		1800	193	1607	1	
	06-18'	2000	200	1800	303	1497	1	
31st July 2017	18-24	2000		1800	193	1607		
1st July 2017 to 31st July 2017	00-24	4500	300	4200	2931	1269		
1st July 2017 to 31st July 2017	00-24				No limit i	s being specified.		
1st July 2017 to 31st July 2017	00-24				No limit i	s being specified.		
	00-05	3800		3300		400		
	05-22	3400	500	2900	2900	0		
1st July 2017 to 31st July 2017	00-24	3800		3300	No limit is			
	00-06				3429	0		
	06-18'	3450	200	3250	3514	0		
51st July 2017	18-24				3429	0		
1st July 2017 to 31st July 2017	00-24				No limit is	s being Specified.		
	00.17	1035		990		765		
1st July 2017 to			45		225			
31st July 2017			.5		223		1	
1st July 2017 to	00-17	1180		1135		1135		
•	17-23	1050	45	1005	0	1005		
318t July 2017	23-24	1180		1135		1135		
1st July 2017 to 31st July 2017	00-24							ort would be revised accordingly) a NLDC website under Intra-
	1st July 2017 to 31st July 2017 1st July 2017	St July 2017 to 31st July 20	Date Time Period (hrs) Transfer Capability (TTC) 1st July 2017 to 31st July 2017 to 31st July 2017 to 31st July 2017 00-06 2000 2000 2000 2000 2000 2000 2000	St July 2017 to 31st July 20	Date Time Period (hrs) Transfer Capability (TTC) Reliability Margin (ATC) Transfer Capability (ATC) 1st July 2017 to 31st July 2017 to 31st July 2017 to 31st July 2017 00-06 2000 06-18′ 2000 1800 1800 1800 2000 1800 1800 1800 1st July 2017 to 31st July 2017 00-24 4500 300 4200 200 300 4200 1st July 2017 to 31st July 20	Time Period (hrs) Capability Capability (TTC) Capability (TTC) Capability (TTC) Capability (TTC) Capability (TTC) Capability (ATC) Capability (ATC)	Strain Capability (hrs) Ca	Part Period (hrs) Period (hrs)

^{*} Fifty Percent (50 %) Counter flow benefit on account of LTA/MTOA transactions in the reverse direction would be considered for advanced transactions (Bilateral & First Come First Serve).

National Load Despatch Centre Total Transfer Capability for July 2017

Issue Date: 27/3/2017 Issue Time: 1800 hrs Revision No. 0

Corridor	Date	Time Period (hrs)	Total Transfer Capability (TTC)	Reliability Margin	Available Transfer Capability (ATC)	Long Term Access (LTA)/ Medium Term Open Access (MTOA) #	Margin Available for Short Term Open Access (STOA)	Changes in TTC w.r.t. Last Revision	Comments
----------	------	-------------------------	--	-----------------------	--	--	--	---	----------

¹⁾ S1 comprises of Telangana, AP and Karnataka; S2 comprises of Tamil Nadu and Puducherry; S3 comprises Kerala

The figure is based on LTA/MTOA approved by CTU and Allocation figures as per RPCs RTA/REA. In actual Operation, due to Units being on Maintenance/Fuel shortage/New units being commissionned the LTA/MTOA utilized would vary. RLDC/NLDC would factor this situation on day-ahead basis. In the eventuality that net schedules exceed ATC, real time curtailments might be effected by RLDCs/NLDC.

In case of TTC Revision due to any shutdown:

- 1) The TTC value will be revised to normal values after restoration of shutdown.
- 2) The TTC value will be revised to normal values if the shutdown is not being availed in real time.

Limiting Constraints

Corridor	Constraint
NR-WR	(n-1) contingency of 400kV Zerda-Bhinmal and (n-1) contingency of 220kV Badod-Modak
WR-NR	1. (n-1) Contingnecy of 765kV Gwalior-Agra one ckt leads to 2750 MW loading on second circuit. 2. High Loading of 400kV Singrauli-Anpara S/C.
NR-ER	(n-1) contingency of 400 kV Saranath-Pusauli
ER-NR	(n-1) contingencies of N.Ranchi - Chandawa S/c & (n-1) contingencies of 400kV MPL- Maithon S/c and high availability of Hydro power
WR-SR & ER-SR	(n-1) contingency of one circuit of 765kV Aurangabad-Sholapur will lead to 874 MW loading on 400kV Vemagiri(PG)-Gazuwaka (With Opening of 400kV Vemagiri(PG)-Nunna S/C) Low Voltage at Gazuwaka (East) Bus
ER-NER	a. (n-1) contingency of 400/220 kV, 2x315 MVA ICTs at Misa b. High loading of 220 kV Sonabil-Samaguri line(200 MW)
NER-ER	a. (n-1) contingency of 400 kV Byrnihat - Bongaigaon line b. High loading of 220 kV Sonabil-Samaguri line(200 MW)
W3 zone Injection	

²⁾ W3 comprises of the following regional entities:

a) Chattisgarh Sell transaction, b) Jindal Power Limited (JPL) Stage-I & Stage-II, c) Jindal Steel and Power Limited (JSPL), d) ACBL, e) LANCO Amarkantak

f) BALCO, g) Sterlite (#1,3,4), h) NSPCL, i) Korba, j) Sipat, k) KSK Mahanadi, L)DB Power, m) KWPCL, n)Vandana Vidyut o)RKM, p)GMR Raikheda, q)Ind Barath and any other regional entity generator in Chhattisgarh

Simultaneous Import Capability

Corridor	Date	Time Period (hrs)	Total Transfer Capability (TTC)	Reliability Margin	Available Transfer Capability (ATC)	Long Term Access (LTA)/ Medium Term Open Access (MTOA)	Margin Available for Short Term Open Access (STOA)	Changes in TTC w.r.t. Last Revision	Comments
ER									
		00-05	12200		11400		518		
		05-08	11400		10600		0		
NR	1st July 2017 to 31st July 2017	08-18	12200	800	11400	10882	518		
	313t July 2017	18-23	10950		10150		0		
		23-24	12200		11400		518		
	1st July 2017 to	00-17	1035	45	990		765		
NER	31st July 2017	17-23	1010		965	225	740		
	21300 413 2017	23-24	1035		990		765		
WR									
		00-05	6850		6100	6132	0		
	SR 1st July 2017 to 31st July 2017	05-06	6850		6100	6132	0		
SR		06-18	6850	750	6100	6217	0		
	, ,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,	18-22	6850		6100	6132	0		
		22-24	6850		6100	6132	0		

^{*} Fifty Percent (50%) Counter flow benefit on account of LTA/MTOA transactions in the reverse direction would be considered for advanced transactions (Bilateral & First Come First Serve).

* For approving STOA Bilateral transactions, margin available in Simultaneous Import of NR would be apportioned on WR-NR Corridor & ER-NR Corridor in the following ratio:

Margin in Simultaneous import of NR = A

WR-NR ATC =B

ER-NR ATC = C

Margin for WR-NR applicants = A * B/(B+C)

Margin for ER-NR Applicants = A * C/(B+C)

Simultaneous Export Capability

Corridor	Date	Time Period (hrs)	Total Transfer Capability (TTC)	Reliability Margin	Available Transfer Capability (ATC)	Long Term Access (LTA)/ Medium Term Open Access (MTOA)	Margin Available for Short Term Open Access (STOA)	Changes in TTC w.r.t. Last Revision	Comments
NR*	1st July 2017 to	00-06 06-18'	4 11 11	700	3800 3800	248 368	3552 3432		
	31st July 2017	18-24	4500		3800	248	3552		
	1 at July 2017 to	00-17	1180	45	1135	0	1135		
NER	1st July 2017 to	17-23	1050		1005		1005		
	31st July 2017	23-24	1180		1135		1135		
WR									

SR*	1st July 2017 to 31st July 2017	00-24		No limit is being Specified.					

^{*} Fifty Percent (50 %) Counter flow benefit on account of LTA/MTOA transactions in the reverse direction would be considered for advanced transactions (Bilateral & First Come First Serve).

Limiting Constraints

	5 0 0 118 0 1 00 111 0 8						
	Import	(n-1) contingencies of N.Ranchi - Chandawa S/c & (n-1) contingencies of 400kV MPL- Maithon S/C and high availability of Hydro power					
NR NER	Import	1. (n-1) Contingnecy of 765kV Gwalior-Agra one ckt leads to 2750 MW loading on second circuit. High Loading of 400kV Singrauli-Anpara S/C.	2.				
	Evnout	n-1) contingency of 400kV Zerda-Bhinmal and (n-1) contingency of 220kV Badod-Modak.					
	Export	(n-1) contingency of 400 kV Saranath-Pusauli					
	Import	a. (n-1) contingency of 400/220 kV, 2x315 MVA ICTs at Misa					
NED		b. High loading of 220 kV Sonabil-Samaguri line(200 MW)					
NEK	T- 4	a. (n-1) contingency of 400 kV Byrnihat - Bongaigaon line	b. High				
	Export	loading of 220 kV Sonabil-Samaguri line(200 MW)					
		(n-1) contingency of one circuit of 765kV Aurangabad-Sholapur will lead to 874 MW loading on 400kV					
SR	Import	Vemagiri(PG)-Gazuwaka (With Opening of 400kV Vemagiri(PG)-Nunna S/C)					
		Low Voltage at Gazuwaka (East) Bus					

National Load Despatch Centre Total Transfer Capability for July 2017

Revision	Date of	Period of	Reason for Revision	Corridor
No	Revision	Revision		Affected

ASSUN	MPTIONS IN BASECASE				
		+	1	Month : July'17	
S.No.	Name of State/Area	Load	†	Generation	
		Peak Load (MW)	Off Peak Load (MW)		Off Peak (MW)
I	NORTHERN REGION	†	†		` '
1	Punjab	10671	9480	4285	4302
	Haryana	8203	8052	1533	1533
	Rajasthan	8264	9534	4458	4458
_	Delhi	5767	6332	940	940
5	Uttar Pradesh	14322	14317	10032	10036
6	Uttarakhand	1869	1634	985	962
7	Himachal Pradesh	1184	1068	921	863
8	Jammu & Kashmir	2359	1498	920	930
9	Chandigarh	327	300	0	0
10	ISGS/IPPs	27	27	19979	18386
	Total NR	52992	52241	44053	42410
II	EASTERN REGION				
1	Bihar	3920	2608	238	238
2	Jharkhand	1193	836	397	337
	Damodar Valley Corporation	2961	2554	4468	3768
4	Orissa	4173	3199	3342	2325
5	West Bengal	8359	5800	5216	4148
6	Sikkim	88	89	0	0
7	Bhutan	245	245	982	982
8	ISGS/IPPs	560	567	11255	8518
	Total ER	21469	15868	25869	20286
	WESTERN BESIGN	 			
	WESTERN REGION	1.10.10	14000	0004	7070
	Maharashtra	14940	11898	9694	7279
	Gujarat	12432	10131	9835	7466
-	Madhya Pradesh	7044	5925	3569	3099
	Chattisgarh	3353	3104	1915	2461
	Daman and Diu	286	279	0	0
	Dadra and Nagar Haveli	740	717	0	0
		399	296	0	0
8	ISGS/IPPs	2701	2844	32655	29850
1 1	Total WR	41896	35194	57668	50154

IV	SOUTHERN REGION				1
1	Andhra Pradesh	7900	7330	6080	5500
2	Telangana	7305	5815	4523	3329
	Karnataka	8717	7530	5689	4314
4	Tamil Nadu	14750	12574	8145	6750
5	Kerala	3450	1780	1499	283
6	Pondy	395	395	0	0
7	Goa-SR	89	89	0	0
8	ISGS/IPPs	0	0	11044	9692
	Total SR	42606	35513	36980	29868
V	NORTH-EASTERN REGION				
1	Arunachal Pradesh	143	89	0	0
2	Assam	1227	1069	240	200
3	Manipur	150	76	0	0
4	Meghalaya	268	200	214	164
5	Mizoram	95	69	8	8
6	Nagaland	122	83	22	16
7	Tripura	254	157	75	75
8	ISGS/IPPs	100	60	2030	1888
	Total NER	2359	1803	2589	2351
	Total All India	161566	140864	168142	146052